
1. Description

- The D1805 is a 60W (P_{SAT}) gallium nitride (GaN) high electron mobility transistor (HEMT) with first generation RF GaN technology from Raytron.
- The D1805 operates from 0.03 to 1.4GHz with a 28V supply rail. It is matched to 50ohm on the input and featured an outstanding input return loss. In typical application like 0.2 to 1.3GHz wideband application, it can deliver 30W CW power.



D1805-PDS-F01

Figure 1. D1805 Package Outline

2. Applications

- Military and Civilian Radar
- Land Mobile and Military Radio Communications
- Avionics and Test Instrumentation

3. Features[1]

- Operating Frequency:0.03–1.4GHz
- Output Power (P_{SAT}): 48dBm (63W)
- Linear Gain: 15.5dB
- Typical DE @P_{SAT}: 74.0%
- Operating Voltage: 28V
- CW and Pulse Capable
- Impedance Matched Z_{IN}=50ohm
- Package Type: 360F-E

[1] Measured in Raytron DEMO @1.2GHz


4. Brief Typical Performance

Table 1. Brief Typical Performance

Parameter	0.2GHz	0.6GHz	1.0GHz	1.3GHz	Units
Linear Gain	15.3	15.2	14.5	14.6	dB
Drain Efficiency	68.5	67.7	54.0	71.7	%
Output Power	44.9	47.9	47.2	47.7	dBm
Output Power	31	61	52	58	W

- Typical Class AB performance in Raytron DEMO_A (0.2-1.3GHz) with the device soldered onto the heatsink, test condition: V_{DS} = 28V, I_{DS} = 200mA, V_{GS} = -2.84V
- Test Condition: CW

5. Block Diagram



D1805-PDS-F02

Figure 2. D1805 Block Diagram

Table of Contents

No.	Contents	Page
1	Description	1
2	Applications	1
3	Features	1
4	Brief Typical Performance	1
5	Block Diagram	1
6	Absolute Maximum Ratings	3
7	Recommended Operating Conditions	3
8	Electrical Characteristics	3
9	Wide-band Application Performance	4
10	Package Outline	5
11	Application Circuit	6
12	DEMO Summary	7
13	Recommended Solder Temperature Profile	8
14	Handling Precautions	8
15	Contact Information	8
16	Disclaimer	9

6. Absolute Maximum Ratings

Table 2. Absolute Maximum Ratings

Parameter	Symbol	Rating	Units
Drain-Source Voltage	V_{DSS}	84	V
Gate-Source Voltage	V_{GS}	-10 ~ +1	V
Operating Voltage	V_{DS}	10 ~ +32	V
Maximum Forward Gate Current	I_{GMax}	9.12	mA
Storage Temperature Range	T_{STG}	-65 ~ +150	°C
Operating Junction Temperature	T_J	250	°C

7. Recommended Operating Conditions

Table 3. Recommended Operating Conditions

Parameter	Min.	Typ.	Max.	Units
Drain-Source Voltage Range, V_{DS}	-	28	32	V
Drain Bias Current, I_{DS}	-	200	-	mA
Gate-Source Voltage, V_{GS}	-	-2.84	-	V
Channel Temperature, T_{CH}	-	-	225	°C

Table 4. Thermal Resistance

Parameter	Symbol	Value	Unit
Thermal Resistance (Active Die Surface-to-Case)[1]	R_{thsc} (IR)	2.00	°C/W
Thermal Resistance (Junction-to-Case)[2]	R_{thjc} (FEA)	2.56	°C/W

1. Thermal Resistance at average power by infrared measurement, Active Die Surface-to-Case, $T_{base\text{-}plate}$ = 85℃, P_D = 45.0W
2. Thermal Resistance at average power by Finite Element Analysis, Junction-to-Case, $T_{base\text{-}plate}$ = 85℃, $T_{junction}$ = 200℃

8. Electrical Characteristics (T_C = 25˚C)

Table 5. DC Characteristics

Parameter	Symbol	Min.	Typ.	Max.	Units
Drain-Source Breakdown Voltage[1] (V_{GS} = -10V, I_{DS} = 9.12mA)	$V_{DS(BR)}$	84	-	-	V
Saturated Drain Current[2] (V_{DS} = 10V, V_{GS} = 1.0V)	I_{Max}	-	10.49	-	A
Gate Threshold Voltage[3] (V_{DS} = 28V, I_{DS} = 9.12mA)	$V_{GS(TH)}$	-3.30	-2.80	-2.30	V
Gate Quiescent Voltage[3] (V_{DS} = 28V, I_{DS} = 200mA)	$V_{GS(Q)}$	-	-2.84	-	V

1. Measured on wafer prior to packaging
2. Scaled from PCM data
3. Typical Class AB performance in Raytron DEMO_A

Table 6. RF Characteristics @ DEMO_A [1,2]

Freq. (GHz)	Linear Gain (dB)	Drain Efficiency (%)	Output Power (dBm)	Output Power (W)
0.2	15.3	68.5	44.9	31
0.5	15.0	60.8	46.4	44
0.8	14.7	66.8	46.4	43
1.1	14.8	51.8	47.7	58
1.3	14.6	71.7	47.7	58

1. Typical Class AB performance in Raytron DEMO_A (0.2-1.3GHz) with the device soldered onto the heatsink, test condition: V_{DS} = 28V, I_{DS} = 200mA, V_{GS} = -2.84V
2. Test Condition: CW

9. Wide-band Application Performance

■ Wide-band Application Performance (DEMO_A: 0.2-1.3GHz)




Figure 3. S11, S21, S22 vs. Freq.




Figure 4. Wide-band Application Gain and DE vs. Output Power




Figure 5. Wide-band Application P_{OUT}, Gain and DE vs. Freq.

- Typical Class AB performance in Raytron Wide-band Application DEMO_A (0.2-1.3GHz) with the device soldered onto the heatsink, test condition: V_{DS} = 28V, I_{DS} = 200mA, V_{GS} = -2.84V
- Test Condition: CW
- The output power is more than 44.9dBm (31W) at 0.2-1.3GHz.

Table 7. RF Characteristics @ DEMO_A

Freq. (GHz)	Linear Gain (dB)	Drain Efficiency (%)	Output Power (dBm)	Output Power (W)
0.2	15.3	68.5	44.9	31
0.3	14.5	57.8	45.1	32
0.4	14.4	52	45.2	33
0.5	15.0	60.8	46.4	44
0.6	15.2	67.7	47.9	61
0.7	14.9	66.0	46.5	45
0.8	14.7	66.8	46.4	43
0.9	14.6	57.6	46.5	44
1.0	14.5	54.0	47.2	52
1.1	14.8	51.8	47.7	58
1.2	14.7	56.1	47.5	56
1.3	14.6	71.7	47.7	58

- Typical Class AB performance in Raytron Wide-band Application DEMO_A (0.2-1.3GHz) with the device soldered onto the heatsink, test condition: V_{DS} = 28V, I_{DS} = 200mA, V_{GS} = -2.84V
- Test Condition: CW
- The output power is more than 44.9dBm (31W) at 0.2-1.3GHz.

10. Package Outline

■ Pin Layout




Figure 6. D1805 Pin Layout

Table 8. Pin Description

Pin	Symbol	Description
1/2	V_G / RF_{IN}	Gate voltage / RF Input
3/4	V_D / RF_{OUT}	Drain voltage / RF Output
5	Flange	Source to be Connected to Ground

■ Mechanical Drawing (Package Type: 360F-E)




Figure 7. D1805 Mechanical Drawing

11. Application Circuit

■ Schematic




Figure 8. D1805 DEMO_A Application Circuit Schematic (0.2-1.3GHz)

Table 9. Bias Procedure

Bias-up Procedure	Bias-down Procedure
1) Set V_{GS} to the pinch-off voltage, typically -6V	1) Turn off RF signal
2) Turn on V_{DS} to nominal supply voltage (28V)	2) Turn off V_{DS}
3) Slowly adjust V_{GS} until I_{DS} current is attained	3) Wait two seconds to allow drain capacitor to discharge
4) Apply RF input power to desired level	4) Turn off V_{GS}

■ Layout




Figure 9. D1805 Application Circuit Layout (0.2-1.3GHz)
(DEMO_A Size: 6.7cm x 3.1cm)

Table 10. Bill of Materials

Component	Value	Description	Manufacturer	Part Number
PCB	20mil	N/A	Rogers	Rogers4350B
C1	1000pF	C0G 250V 0603 Capacitor	Murata	GCM1885C2A102JA16
C2	0.1uF	X7R 100V 1206 Capacitor	Murata	GRM3195C2A104JA01
C3	1.0uF	X7R 100V 1210 Capacitor	Murata	GRM32ER72A105KA01
C4	1.4pF	C0G 250V 0805 Capacitor	Murata	GQM2195C2E1R4BB12
C5	4.5pF	C0G 250V 0805 Capacitor	Murata	GQM2195C2E4R5BB12
C6	1.4pF	C0G 250V 0805 Capacitor	Murata	GQM2195C2E1R4BB12
C7	0.3pF	C0G 250V 0805 Capacitor	Murata	GQM2195C2ER30WB12
C8	2.3pF	C0G 250V 0805 Capacitor	Murata	GQM2195C2E2R3BB12
C9	100uF	80V 100uF	Nichicon	UBW1K101MPD1TD
R1	10Ω	1/8W 0805 Resistor	Yageo	RC0805FR-0710RL
L1	10nH	1.6A 0603 Inductor	Murata	LQW18AN10NG80D
L2	N/A	10turn, D=12mm, d=1.6mm	N/A	N/A

12. DEMO Summary

Table 11. DEMO Summary

D1805 DEMO Name	V_{DS} (V)	Freq (GHz)	Linear Gain(dB)	P_{SAT} (dBm)	P_{SAT} (W)	Drain Efficiency(%)	Pulse or CW
DEMO_A, 30W	28	0.2-1.3	14.4	44.9	31	51.8%	CW

13. Recommended Solder Temperature Profile




Figure 10. Recommended Solder Temperature Profile

14. Handling Precautions

- **ESD Caution**

  ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore proper ESD precautions should be taken to avoid performance degradation or loss of functionality.



15. Contact Information

For the latest specifications, additional product information, technical support and sales support, please contact:

- **Email:** RF.support@raytrontek.com
- **Web:** www.raytrontek.com

16. Disclaimer

The information provided here is believed to be reliable at the time of publication. Raytron reserves the right to make changes to its products, specifications and product descriptions at any time without notice. Raytron assumes no responsibility for the use of this information and all such information should entirely be at the user's own risk. Raytron makes no warranty about the suitability of its products for specific purpose or application and disclaims all liability, including without limitation consequential and incidental damages. Raytron does not authorize or warrant any Raytron products for use in the life support devices or systems.

Raytron Microwave
Copyright @ Raytron Technology Co., Ltd.