
1. Description

- The F7302 is a wideband GaAs low phase noise amplifier for wireless application. It is internally integrated with an active bias circuity and can provide stable current over temperature and process variation.
- The F7302 is a high linearity gain block for application that require small in size with minimal number of external components. It is internally matched to 50Ω at input and output.



F7302-PDS--F01

Figure 1. F7302 Package Outline

2. Applications

- Data Link Communication
- Radar
- Small Cell
- Private Communication Network

3. Features[1]

- Operating Frequency: 10-6000MHz
- Output Power (P1dB): 16.2dBm
- Small Signa Gain: 15.3dB
- Phase Noise:-169dBc/Hz@10KHz Offset
- Operating Voltage: 5V
- Package: SOT-89

[1]. Measured in Raytron DEMO @1000MHz

4. Brief Typical Performance

Table 1. Brief Typical Performance


Parameter	1000MHz	Units
Small Signal Gain[1]	15.3	dB
Output P1dB[2]	16.2	dBm
Output IP3[3]	31.3	dBm

[1]. V_{CC}=5V, I_{CQ}=50mA,Temp=25℃, 50Ω test system

[2]. Input signal: CW

[3]. Input signal: 2-tone, P_{IN}=0dBm/tone, Δf=1MHz

5. Block Diagram



F7302-PDS-F02

Figure 2. F7302 Block Diagram TOP View

Table of Contents

No.	Contents	Page
1	Description	1
2	Applications	1
3	Features	1
4	Brief Typical Performance	1
5	Block Diagram	1
6	Absolute Maximum Ratings	3
7	Recommended Operating Conditions	3
8	Electrical Characteristics	3
9	Phase Noise	4
10	Typical Performance	5
11	Package Outline	5
12	Application Circuit	6
13	Handling Precautions	8
14	Contact Information	8
15	Disclaimer	9

6. Absolute Maximum Ratings

Table 2. Absolute Maximum Ratings

Parameter	Symbol	Rating	Units
Operating Voltage	V_{CC}	5.5	V
Input Power	P_{IN}	25	dBm
Storage Temperature Range	T_{STG}	- 55 ~ +125	°C
Operating Junction Temperature	T_J	150	°C

7. Recommended Operating Conditions

Table 3. Recommended Operating Conditions

Parameter	Min.	Typ.	Max.	Units
Operating Temperature Range	-50	25	105	°C
Operating Voltage	-	5.0	5.5	V
Operating Frequency	10	-	6000	MHz

8. Electrical Characteristics (T_C = 25°C)

Table 4. Electrical Characteristics (V_{CC}=5V, L1=51nH, I_{CQ}=50mA, T_C=25℃, 50Ω test system)

Parameter	Conditions	Min.	Typ.	Max.	Units
Frequency	-	500	-	6000	MHz
Small Signal Gain	500MHz	-	15.2	-	dB
	1000MHz	-	15.3	-	dB
	2000MHz	-	15.0	-	dB
	3000MHz	-	14.7	-	dB
	4000MHz	-	14.1	-	dB
	5000MHz	-	13.3	-	dB
Input Return Loss	1000MHz	-	17.2	-	dB
Output Return Loss	1000MHz	-	19.0	-	dB
Output P1dB	500MHz	-	16.1	-	dBm
	1000MHz	-	16.2	-	dBm
	2000MHz	-	15.1	-	dBm
	3000MHz	-	13.0	-	dBm
	4000MHz	-	10.9	-	dBm
Output IP3 P_{OUT}=0dBm/tone, Δf=1MHz	500MHz	-	32.1	-	dBm
	1000MHz	-	31.4	-	dBm
	2000MHz	-	28.0	-	dBm
	3000MHz	-	24.3	-	dBm
	4000MHz	-	21.1	-	dBm
Device Operating Current	-	-	50	-	mA

9. Phase Noise

Table 5. Electrical Characteristics (V_{CC}=5V, L1=330nH, I_{CQ}=48mA, T_C=25℃, 50Ω test system)

Parameter	Conditions	Min.	Typ.	Max.	Units
Frequency	-	100	-	2000	MHz
Small Signal Gain	100MHz	-	15.4	-	dB
	500MHz	-	15.4	-	dB
	1000MHz	-	15.3	-	dB
	1500MHz	-	15.2	-	dB
	2000MHz	-	14.8	-	dB
Input Return Loss	1000MHz	-	17.9	-	dB
Output Return Loss	1000MHz	-	21.4	-	dB
Output P1dB	100MHz	-	15.3	-	dBm
	500MHz	-	15.6	-	dBm
	1000MHz	-	15.3	-	dBm
	1500MHz	-	14.8	-	dBm
	2000MHz	-	14.0	-	dBm
Output IP3 P_{OUT}=0dBm/tone, Δf=1MHz	100MHz	-	29.4	-	dBm
	500MHz	-	30.7	-	dBm
	1000MHz	-	30.0	-	dBm
	1500MHz	-	28.6	-	dBm
	2000MHz	-	26.7	-	dBm
Device Operating Current	-	-	48	-	mA

Table 6. Electrical Characteristics (V_{CC}=5V, L1=4.7uH, I_{CQ}=45mA, T_C=25℃, 50Ω test system)

Parameter	Conditions	Min.	Typ.	Max.	Units
Frequency	-	20	-	1200	MHz
Small Signal Gain	20MHz	-	15.7	-	dB
	100MHz	-	15.7	-	dB
	500MHz	-	15.5	-	dB
	1200MHz	-	14.7	-	dB
Input Return Loss	500MHz	-	19	-	dB
Output Return Loss	500MHz	-	20.6	-	dB
Output P1dB	20MHz	-	15.6	-	dBm
	100MHz	-	15.6	-	dBm
	500MHz	-	15.5	-	dBm
	1200MHz	-	13.5	-	dBm
Output IP3 P_{OUT}=0dBm/tone, Δf=1MHz	20MHz	-	29.8	-	dBm
	100MHz	-	30.3	-	dBm
	500MHz	-	30.5	-	dBm
	1200MHz	-	27.5	-	dBm
Device Operating Current	-	-	45	-	mA

Table 7. Phase Noise

Offset Frequency (Hz)		1K	10K	100K	1M
Phase Noise(dBc/Hz)[1]	RFfreq=100MHz	-163	-167	-167	-168
	RFfreq=500MHz	-156	-162	-165	-170
	RFfreq=1000MHz	-162	-169	-170	-171
	RFfreq=1500MHz	-162	-168	-170	-170
	RFfreq=2000MHz	-156	-162	-166	-169

[1]. Test Condition: RF Input Power=IP1dB, L1=330nH

10. Typical Performance




Figure 3. Small Signal S-Parameters vs. Freq.(500-6000MHz)

11. Package Outline

■ Pin Layout




Figure 4. F7302 Pin Layout

Table 8. Pin Description

Pin	Symbol	Description
1	RF_{IN}	RF Input. External DC Block capacitor required.
3	RF_{OUT}/BIAS	RF Output and DC supply input. External DC Block capacitor required.
2/4	GND	RF/DC ground

■ Mechanical Drawing




Figure 5. F7302 Mechanical Drawing

12. Application Circuit

■ Schematic




Figure 6. F7302 Application Circuit Schematic

■ Layout




Figure 7. F7302 Application Circuit Layout

Table 9. Bill of Materials (20-1200MHz)

Component	Value	Description	Manufacturer	Part Number
PCB	20mil	N/A	Rogers	RO4350B
Q1	N/A	F7302 Amplifier, SOT-89 pkg.	Raytron	F7302
C1	2.2uF	0603 Capacitor	Various	N/A
C2	2.2uF	0603 Capacitor	Various	N/A
C3	10.0pF	C0G 250V 0603 Capacitor	Murata	GQM1875C2E100GB12
C4	1.0nF	0603 Capacitor	Various	N/A
C5	2.2uF	0603 Capacitor	Various	N/A
C6	N/A	N/A	N/A	N/A
L1	4.7uH	1008 Inductance	Murata	LQW2UAS4R7J00L
R1	22.0Ω	1/4W 0603 Resistor	Various	N/A

Table 10. Bill of Materials (100-2000MHz)

Component	Value	Description	Manufacturer	Part Number
PCB	20mil	N/A	Rogers	RO4350B
Q1	N/A	F7302 Amplifier, SOT-89 pkg.	Raytron	F7302
C1	1.0nF	0603 Capacitor	Various	N/A
C2	1.0nF	0603 Capacitor	Various	N/A
C3	10.0pF	C0G 250V 0603 Capacitor	Murata	GQM1875C2E100GB12
C4	1.0nF	0603 Capacitor	Various	N/A
C5	2.2uF	0603 Capacitor	Various	N/A
C6	N/A	N/A	N/A	N/A
L1	330.0nH	High Q 0603 Inductance	Murata	LQW18ANR33G80D
R1	22.0Ω	1/4W 0603 Resistor	Various	N/A

Table 11. Bill of Materials (500-6000MHz)

Component	Value	Description	Manufacturer	Part Number
PCB	20mil	N/A	Rogers	RO4350B
Q1	N/A	F7302 Amplifier, SOT-89 pkg.	Raytron	F7302
C1	1.0nF	0603 Capacitor	Various	N/A
C2	1.0nF	0603 Capacitor	Various	N/A
C3	10.0pF	C0G 250V 0603 Capacitor	Murata	GQM1875C2E100GB12
C4	1.0nF	0603 Capacitor	Various	N/A
C5	2.2uF	0603 Capacitor	Various	N/A
C6	N/A	N/A	N/A	N/A
L1	51.0nH	High Q 0603 Inductance	Murata	LQW18AN51NG80D
R1	22.0Ω	1/4W 0603 Resistor	Various	N/A

13. Handling Precautions

■ ESD Caution

Table 12. ESD/MSL Rating

Parameter	Rating	Standard
ESD – Human Body Model (HBM)	Class 1C	ESDA / JEDEC JS-001-2014
ESD – Charged Device Model (CDM)	Class C3	ESDA / JEDEC JS-002-2014
MSL – Moisture Sensitivity Level	Level 3	IPC/JEDEC J-STD-020

ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore proper ESD precautions should be taken to avoid performance degradation or loss of functionality.



14. Contact Information

For the latest specifications, additional product information, technical support and sales support, please contact:

- **Email:** RF.support@raytrontek.com
- **Web:** www.raytrontek.com

15. Disclaimer

The information provided here is believed to be reliable at the time of publication. Raytron reserves the right to make changes to its products, specifications and product descriptions at any time without notice. Raytron assumes no responsibility for the use of this information and all such information should entirely be at the user's own risk. Raytron makes no warranty about the suitability of its products for specific purpose or application and disclaims all liability, including without limitation consequential and incidental damages. Raytron does not authorize or warrant any Raytron products for use in the life support devices or systems.

Raytron Microwave
Copyright @ Raytron Technology Co., Ltd.