
1. Description

- The M0035 is a wideband, 1-bit Digital Controlled Delay Line operating from 5 to 13GHz. It provides true time delay (TTD) functionality with a precise 832ps. The device maintains an insertion loss of -14dB and achieves return loss better than -15dB, making it an ideal solution for advanced RF and microwave systems requiring precise time control.



M0035-PDS-F01

Figure 1. M0035 Functional Block Diagram

2. Applications

- TX/RX Modules
- Radar
- Defense
-

3. Features

- Frequency Range: 5-13GHz
- Time Delay: 832ps
- Insertion Loss: 14dB
- Input/Output Return Loss: -15dB
- Control Voltage: 0/+5V
- Die Size: 2 x 4.4 x 0.1mm

4. Brief Typical Performance

Table 1. Brief Typical Performance

Parameter	5-13GHz	Units
Time Delay	832	ps
Insertion Loss	14	dB
Input/Output Return Loss	-15	dB
Time Delay Error	±15	ps
Amplitude Error	±1	dB

Table of Contents

No.	Contents	Page
1	Description	1
2	Applications	1
3	Features	1
4	Brief Typical Performance	1
5	Recommended Operating Conditions	3
6	RF Characteristics	3
7	Typical Performance Curve	3
8	Outline Dimensions	5
9	Assembly Information	6
10	Handling Precautions	7
11	Contact Information	7
12	Disclaimer	7

5. Recommended Operating Conditions

Table 2. Recommended Operating Conditions

Parameter	Min.	Typ.	Max.	Units
Operating Temperature Range	-55	25	125	°C
Control Voltage, V1	-	0/5	-	V
Reference Voltage, VS	-	-5	-	V

6. RF Characteristics (T_C = 25˚C)

Table 3. RF Characteristics[1]

Parameter	Symbol	Min.	Typ.	Max.	Units
Time Delay	TD		832		ps
Insertion Loss	IL		14		dB
Input Return Loss	RL_{IN}		-15		dB
Output Return Loss	RL_{OUT}		-15		dB
Time Delay Error	Error		±15		ps
Amplitude Error	ΔIL		±1		dB

[1]. Test condition: Input signal CW

7. Typical Performance Curve

■ Small-signal Characteristics Curve




Figure 2. Full state Insertion Loss Characteristics




Figure 3. Full state Input Return Loss Characteristics




Figure 4. Full state Output Return Loss Characteristics




Figure 5. Time Delay Characteristics





Figure 6. Amplitude Error Characteristics

8. Outline Dimensions



Dimensions shown in micrometre

Figure 7. M0035 Outline Dimensions

Table 4. Pad Description

Pad	Symbol	Description
1	RFIN	RF Input
2	RFOUT	RF Output
3	V1	Control Voltage
4	VS	-5V Driver Power Supply

Table 5. Truth Table

	V1	VS
0(Reference)	0V	-5V
832ps	5V	-5V

9. Assembly Information

■ Assembly Diagram




Figure 8. M0035 Assembly Diagram

- **Eutectic Die Attach:** It is best to use an 80% Au/20% Sn preform. Do not expose the chip to a temperature greater than 300°C for more than 30sec.
- **Wire Bonding:** RF bonds made with 1mil gold wire are recommended for the RF ports. Keep all bonds as short as possible, less than 0.35mm.

10. Handling Precautions

- **Storage**
  All bare dies ship in either Waffle or Gel Pak, which is an ESD protective container, and then sealed in an ESD protective bag. After opening the sealed ESD protective bag, all dies must be stored in a dry nitrogen environment.
- **Cleanliness**
  Handle the dies in a clean environment. Never use liquid cleaning systems to clean the dies.
- **ESD Caution**
  ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore proper ESD precautions should be taken to avoid performance degradation or loss of functionality.



11. Contact Information

For the latest specifications, additional product information, technical support and sales support, please contact:

- **Email:** RF.support@raytrontek.com
- **Web:** www.raytrontek.com

12. Disclaimer

The information provided here is believed to be reliable at the time of publication. Raytron reserves the right to make changes to its products, specifications and product descriptions at any time without notice. Raytron assumes no responsibility for the use of this information and all such information should entirely be at the user's own risk. Raytron makes no warranty about the suitability of its products for specific purpose or application and disclaims all liability, including without limitation consequential and incidental damages. Raytron does not authorize or warrant any Raytron products for use in the life support devices or systems.

Raytron Raytron Microwave

Copyright @ Raytron Technology Co.,Ltd