1. Description

- The M2620 is a Ku band power amplifier manufactured using a 0.12μm gate-length gallium nitride high electron mobility transistor (HEMT) process on SiC.
- Operation between 13.4-16.5GHz, the M2620 provides 12W of saturated output power and 23dB of large-signal gain while achieving 35% power-added efficiency.
- To simplify system integration, the M2620 is fully matched to 50ohms with integrated DC blocking caps on both I/O ports.
- The M2620 is grounded through backside metal via holes.
- The M2620 is 100% DC and RF tested on-wafer.




Figure 1. M2620 Functional Block Diagram

2. Applications

- TX/RX Modules
- Wireless Communications

3. Features

- Operating Frequency: 13.4-16.5GHz
- Output Power (P_{SAT}): 41dBm (12W)
- Power Gain: 23dB
- Typical Power Added Efficiency: 35%
- Operating Bias: 28V (V_D), I_{DQ}=220mA
- Small Signal Gain: 29dB
- Input Return Loss: -10dB
- Die Size: 3.59 x 1.75 x 0.05mm

4. Brief Typical Performance

Table 1. Brief Typical Performance

Parameter	13.4~16.5GHz	Units
Output Power	41	dBm
Power Gain	23	dB
Power Added Efficiency	35	%
Drain Dynamic Current	1.55	A
Small Signal Gain	29	dB
Input Return Loss	-10	dB

- Test condition: Input signal and V_D CW

Table of Contents

No.	Contents	Page
1	Description	1
2	Applications	1
3	Features	1
4	Brief Typical Performance	1
5	Absolute Maximum Ratings	3
6	Recommended Operating Conditions	3
7	RF Characteristics	3
8	Typical Performance Curve	4
9	Outline Dimensions	5
10	Assembly Information	6
11	Handling Precautions	6
12	Contact Information	7
13	Disclaimer	7

5. Absolute Maximum Ratings

Table 2. Absolute Maximum Ratings

Parameter	Symbol	Rating	Units
Drain-Source Voltage	V_{DSS}	32	V
Gate-Source Voltage	V_{GS}	-1.9	V
Operating Voltage Range	V_{DS}	0 ~ +32	V
Maximum Input Power	P_{IN}	29	dBm
Maximum Forward Gate Current	I_{GMax}	10	mA
Storage Temperature Range	T_{STG}	- 65 ~ +150	°C
Operating Junction Temperature	T_J	250	°C

6. Recommended Operating Conditions

Table 3. Recommended Operating Conditions

Parameter	Min.	Typ.	Max.	Units
Operating Temperature Range	-55	25	85	°C
Drain-Source Voltage Range, V_{DSS}	-	28	-	V
Drain Bias Current, I_{DQ}	-	220	-	mA
Gate-Source Voltage, V_{GS}	-2.2	-2.05	-1.9	V

7. RF Characteristics (T_C = 25˚C)

Table 4. RF Characteristics

Parameter	Symbol	Min.	Typ.	Max.	Units
Output Power	P_{SAT}	40.5	41	42.5	dBm
Power Gain	G_P	22.5	23	24.5	dB
Power Added Efficiency	PAE	30	35	40	%
Drain Dynamic Current	I_D	1.4	1.55	1.6	A
Small Signal Gain	G_{SS}	25	29	35	dB
Input Return Loss	S11	-	-	-10	dB

- Test condition: Input signal and V_D CW

8. Typical Performance Curve

■ Small Signal Characteristics Curve (T_C = 25˚C)

(V_D=28V, V_G =-2.05V，P_{IN}=-25dBm，CW)




Figure 2. Small Signal Gain vs. Frequency




Figure 3. Input Return Loss vs. Frequency

■ Power Characteristic Curve

（V_D=28V, V_G=-2.05V，P_{IN}=18dBm，CW）




Figure 4. Output Power vs. Frequency




Figure 5. Power Added Efficiency vs. Frequency




Figure 6. Power Gain vs. Frequency





Figure 7. Drain Dynamic Current vs. Frequency

9. Outline Dimensions



- Dimensions shown in micrometre

Figure 8. M2620 Outline Dimensions

Table 5. Pad Description

Pad	Symbol	Description
1	RF_{IN}	RF Input. 50Ohms. DC blocking capacitor is not required.
2	RF_{OUT}	RF Output. 50Ohms. DC blocking capacitor is not required.
3,4	V_D	Drain Voltage stage1&2&3. Bypass network required, refer to figure 9.
5,6	V_G	Gate Voltage stage1&2&3. Bypass network required, refer to figure 9.

10. Assembly Information

■ Assembly Diagram




Figure 9. M2620 Assembly Diagram

- **Eutectic Die Attach:** It is best to use an 80% Au/20% Sn preform. Do not expose the chip to a temperature greater than 300°C for more than 30sec.
- **Wire Bonding:** RF bonds made with 1mil gold wire are recommended for the RF ports.

11. Handling Precautions

■ Storage

All bare dies ship in either Waffle or Gel Pak, which is an ESD protective container, and then sealed in an ESD protective bag. After opening the sealed ESD protective bag, all dies must be stored in a dry nitrogen environment.

■ Cleanliness

Handle the dies in a clean environment. Never use liquid cleaning systems to clean the dies.

■ ESD Caution

ESD (electrostatic discharge) sensitive device. Charged devices and circuit boards can discharge without detection. Although this product features patented or proprietary protection circuitry, damage may occur on devices subjected to high energy ESD. Therefore proper ESD precautions should be taken to avoid performance degradation or loss of functionality.



12. Contact Information

For the latest specifications, additional product information, technical support and sales support, please contact:

- **Email:** RF.support@raytrontek.com
- **Web:** www.raytrontek.com

13. Disclaimer

The information provided here is believed to be reliable at the time of publication. Raytron reserves the right to make changes to its products, specifications and product descriptions at any time without notice. Raytron assumes no responsibility for the use of this information and all such information should entirely be at the user's own risk. Raytron makes no warranty about the suitability of its products for specific purpose or application and disclaims all liability, including without limitation consequential and incidental damages. Raytron does not authorize or warrant any Raytron products for use in the life support devices or systems.

.

Raytron Microwave

Copyright @ Raytron Technology Co.,Ltd.